



# HomeWizard P1 Meter.

## HWE-P1

### Technical specifications.

<b>Weight</b>	60 g
<b>Dimensions</b>	88 × 46 × 15 mm
<b>SKU</b>	HWE-P1
<b>Compatibility</b>	The P1 Meter supports most modern meters in Europe, including SMR 2.2 and newer. Click <a href="#">here</a> to check if the P1 Meter fits your smart meter.
<b>Phases</b>	1 & 3 Phases
<b>Connection</b>	Wi-Fi 2.4GHz b/g/n
<b>Usage</b>	IP51 (indoor)
<b>Power consumption</b>	< 1 W
<b>Power supply</b>	No external power supply needed on SMR5 smart meters. USB-C power supply required for older smart meters (sold separately)
<b>Measurements</b>	Electricity import/export, gas
<b>Data frequency</b>	Electricity up to every second, gas per 5 minutes (on SMR5 smart meters)
<b>Data encryption</b>	Yes
<b>Local API</b>	Yes
<b>Bridge/hub required</b>	No
<b>History</b>	Energy usage history of the past 12 months Extend your energy usage history with an Energy+ subscription

Version: January 2026

[www.homewizard.com](http://www.homewizard.com)

HomeWizard B.V. | Keyeserswey 79, 2201 CX, Noordwijk, The Netherlands  
Registration number (NL): 53733983 | VAT: NL850995188B01